
Socket; 2-pole; Cod. B; 4,00 mm²; gray

www.wago.com/770-242







Item description

- Protected against mismating and maintenance-free
- Push-in CAGE CLAMP® spring pressure connection technology allows solid conductors to be simply pushed into a unit
- Two-wire connection per pole for loops or bridges
- Components can be clearly printed on and color-coded to meet custom requirements

Note:

All connectors for mounted installations (snap-in versions for lighting fixtures or devices, all types of PCB and distribution connectors) are factory-equipped with locking levers to ensure plugs and sockets are securely locked. Additional locking levers are only required for flying leads (plug /socket).

Note on mismating protection:

All WINSTA® components are 100% protected against mismating when:

- a.) plugging different numbers of poles
- b.) plugging while rotated 180
- c.) plugging while laterally staggered
- d.) plugging one pole

Safety information 1:

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/770-242



Application note for the U.S. market (USR): Some versions may also be used for current interruption in accordance with the UL certificate in select applications with currents below 16 A and voltages up to 600 V. For further information, please contact your local sales office.

Data

Electrical data

Note on Contact Resistance approx. 1 m Ω of contact resistance approx. 0.25 m Ω contact transition plug/socket

Ratings per IEC/EN 60664-1

Ratings per	IEC/EN 60664-1
Rated voltage (III / 3)	250 V
Rated impulse voltage (III / 3)	4 kV
Rated current	25 A
Legend (ratings)	(III / 3) ≙ Overvoltage category III / Pollution degree 3

Approvals per UL 1977

Rated voltage per UL 1977 (factory wiring only)	600 V
Rated current per UL 1977 (factory wiring only)	23 A

Connection data

Connection technology	Push-in CAGE CLAMP®
Actuation type	Operating tool
	Push-in
Nominal cross section	4 mm²
Solid conductor	0,5 4 mm² / 20 12 AWG
Solid conductor, push-in termination	1,5 4 mm² / 16 12 AWG
Stranded conductor	0,5 2,5 mm² / 20 14 AWG
Fine-stranded conductor	0,5 4 mm² / 20 12 AWG
Fine-stranded conductor with ferrule with plastic collar	0,25 1,5 mm² / 20 16 AWG
Fine-stranded conductor with ferrule without plastic collar	0,25 2,5 mm² / 20 14 AWG
Fine-stranded conductor with ferrule, push-in termination, from	1,5 mm² / 16 AWG
Strip length	9 mm / 0.35 inch
Note (strip length)	see also packaging or instructions
No. of poles	2
Total number of connection points	4
Total number of potentials	2
Conductor entry direction to mating direction	0°

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/770-242



Geometrical Data

Pin spacing	10 mm / 0.394 inch
Width	20 mm / 0.787 inch
Height	12,9 mm / 0.508 inch
Depth	37,5 mm / 1.476 inch

В

Mechanical data

Coding

Mating force of a plug-in connection	approx. 20 70 N (depending on pole number)
Retention force of a plug-in connection	Locked: > 80 N
Unmating force of a plug-in connection	Unlocked: approx. 20 70 N (depending on pole number)
Number of mating cycles	200, without resistive load
	100, with resistive load $I_N = 25 \text{ A}$, tested (4 mm ² /AWG 12)
Marking	12
Protection class	IP20
Note on protection class	In mated condition with strain relief housing: IP2xC (These compact connectors are not designed for use in open, easily accessible areas.)
Potential marking	12

Plug connection

Contact type (pluggable connector)	Female connector/socket
Connector connection type	for conductor
Mismating protection	Yes
Locking of plug-in connection	locking lever
Locking lever	retrofittable

Material Data

Color	gray
Insulating material	Polyamide 66 (PA 66)
Clamping spring material	Chrome nickel spring steel (CrNi)
Contact material	Copper or copper alloy (surface-treated)
Fire load	0.114 MJ

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

www.wago.com/770-242



Weight		6.6 g	
Environme	ntal Requirements		
	•	E 140°C	
	temperature	-5 +40 °C -35 +85 °C	
	operating temperature		
Note on Col	ntinuous Service Temperature	Insulating parts for temperatures ≤ 105 °C	
Commercia	al data		
Product Gro	pup	20 (WINSTA)	
Packaging t	ype	BOX	
Country of o	origin	DE	
GTIN		4050821541912	
Customs Ta	ariff No.	85366990990	
Annrovals	/ Certificates		
	sific Approvals		
Country spec	Silic Approvais		Certificate
Logo	Approval	Additional Approval Text	name
	CCA	EN 61984	2173495.01
KEMA	DEKRA Certification B.V.		
Ship Approva	als		
			Certificate
Logo	Approval	Additional Approval Text	name
ABS.	ABS	-	19-
	American Bureau of Shipping		HG1868589-
ALPANDONED PRES			PDA
	DNV GL		TAE00001Z6
THE REPROVED AND DELL	Det Norske Veritas, Germanischer Lloyd		17120000120
DNV·GL	•		
MARITIME			
	LR Lloyds Register	IEC 61984	02/20050 (E6)
THE AMERICAL SCHOOL	Lioyus Registei		(E0)
UL-Approvals	5		Certificate
Subject to cha	anges. Please also observe the further product docu	mentation!	Gertinoate
WAGO Kontal	kttechnik GmbH & Co. KG	Do you have any questions about our products?	
Hansastr. 27		We are always happy to take your call at +49 (571)	887-44222.
32423 Minder	n		

www.wago.com/770-242



Approval Additional Approval Text Logo name

> cURus UL 1977 E45171 Sec. 9

Underwriters Laboratories Inc.



Counterpart



Item no.770-1601 T-distribution connector; 2-pole; Cod. B; 1 input; 2 outputs; 2 locking levers; gray

www.wago.com/770-1601



Item no.770-1608

h-distribution connector; 2-pole; Cod. B; 1 input; 2 outputs; outputs on both sides; 2 locking levers; www.wago.com/770-1608



Item no.770-1651

www.wago.com/770-1651 h-distribution connector; 2-pole; Cod. B; 1 input; 2 outputs; outputs on one side; 2 locking levers; gray



Item no.770-1658

h-distribution connector; 2-pole; Cod. B; 1 input; 2 outputs; outputs on both sides; 3 locking levers; www.wago.com/770-1658 for flying leads; gray



Item no.770-1701

T-distribution connector; 2-pole; Cod. B; 1 input; 2 outputs; 3 locking levers; for flying leads; gray

www.wago.com/770-1701



Item no.770-1704

3-way distribution connector; 2-pole; Cod. B; 1 input; 3 outputs; gray

www.wago.com/770-1704



Item no.770-1751

h-distribution connector; 2-pole; Cod. B; 1 input; 2 outputs; outputs on one side; 3 locking levers; for www.wago.com/770-1751 flying leads; gray



Item no.770-252

www.wago.com/770-252 Plug; 2-pole; Cod. B; 4,00 mm²; gray



Item no.771-8992/005-103

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

www.wago.com/770-242



pre-assembled interconnecting cable; Socket/plug; 2-pole; Cod. B; Control cable 2 x 1.0 mm 2 ; 1 m; 1,00 mm 2 ; gray

www.wago.com/771-8992 /005-103

K DO

Item no.771-8992/205-103

pre-assembled connecting cable; Plug/open-ended; 2-pole; Cod. B; Control cable 2 x 1.0 mm 2 ; 1 m; 1,00 mm 2 ; gray

www.wago.com/771-8992 /205-103

Compatible products

General accessories

44	Item no.: 770-317	
A (2)	Snap-in frame; 2-pole; 0.5 2.0 mm; black	www.wago.com/770-317
0.00	Item no.: 770-337	WWW.Wago.com/770.227
AN AS	Snap-in frame; 2-pole; 0.5 2.0 mm; black	www.wago.com/770-337
ools		
9	Item no.: 210-719	www.wago.com/210-719
	Operating tool; Blade: 2.5 x 0.4 mm; with a partially insulated shaft	www.wago.com/210-719
	Item no.: 770-382	www.waga.com/770.202
1	Operating tool; 2-way; green	www.wago.com/770-382
protection		
-	Item no.: 770-201	www.wago.com/770-201
4,	Lockout cap; 12-pole, separable; 12-pole; for sockets; black	www.wago.com///0-201
~	Item no.: 770-221	
4.	Lockout cap; for socket; 12-pole; separable; white	www.wago.com/770-221
Strain relief	plate	
44	Item no.: 770-502/041-000	www.wago.com/770-502
3 3	Strain relief housing; 2-pole; with locking clip; for 1 cable; 7.0 10.5 mm; 35 mm; black	/041-000
4.4	Item no.: 770-502/042-000	www.wago.com/770-502
3 3	Strain relief housing; 2-pole; with locking clip; for 1 cable; 5.0 9.0 mm; 35 mm; black	/042-000
44	Item no.: 770-512/041-000	www.wago.com/770-512
	Strain relief housing; 2-pole; with locking clip; for 1 cable; 7.0 10.5 mm; 35 mm; white	/041-000
44	Item no.: 770-512/042-000	www.wago.com/770-512
STREET, STREET,	Strain relief housing; 2-pole; with locking clip; for 1 cable; 5.0 9.0 mm; 35 mm; white	/042-000

 $\label{thm:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

www.wago.com/770-242



Locking lever

Ø	Item no.: 770-101 Locking lever; for flying leads; for manual operation; black	www.wago.com/770-101
◆	Item no.: 770-111 Locking lever; for flying leads; for tool operation; black	www.wago.com/770-111
()	Item no.: 770-121 Locking lever; for flying leads; for manual operation; white	www.wago.com/770-121
0	Item no.: 770-131 Locking lever; for flying leads; for tool operation; white	www.wago.com/770-131

Downloads Documentation

Bid Text

770-242 GAEB X81 - Datei	Feb 19, 2019	xml 3.0 kB	Download
770-242 doc - Datei	Jun 8, 2015	doc 24.1 kB	Download

CAD/CAE-Data

CAD data

2D/3D Models 770-242	URL	Download
CAE data		
EPLAN Data Portal 770-242	URL	Download
WSCAD Universe 770-242	URL	Download

Installation Notes

32423 Minden

Conductor termination


Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27


Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com

www.wago.com/770-242






1. Strip length, outer insulation = 35 mm (2-pole), 55 mm (3- to 5-pole)




To terminate fine-stranded conductors, open the clamping unit via screwdriver (2.5 mm blade width) and insert stripped conductor until it hits backstop.



Insert stripped solid conductor until it hits backstop.

2. Strip length = 9 mm

3. Extended ground conductor = 8 mm



To terminate fine-stranded conductors, open the clamping unit via screwdriver (2.5 mm blade width) and insert stripped conductor until it hits backstop.


Conductor removal

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com


www.wago.com/770-242






To remove the conductor, actuate the clamp via screwdriver (2.5 mm blade width) and pull out the conductor.


Installation



We recommend pulling the pre-latched strain relief housing over the cable prior to termination. However, the strain relief can be mounted at a later time as well.



Latch the strain relief housing on the plug /socket. Note the "TOP" inscription.



Prepare strain relief housing by snapping together upper and bottom part.



Tighten strain relief screw via screwdriver (2.5 mm blade width).

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com


www.wago.com/770-242



Coding



Simply cut off the coding pin from the socket.




Insert coding pin into plug (break first) until it engages.

Mismating protection



B-coded connectors with different colors can be plugged together.



B-coded connectors (shown in gray) not only differ in color, but also in their design, making them incompatible with other coded connectors.



Easy circuit identification via different marking and colors

Important note:

Different colors and/or pole marking are used for circuit identification.

Only connectors of the same color and same pole marking must be plugged together.

Product family

<i>WINSTA</i>
MIDI special
Show all products from the family

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com