




Data sheet | Item number: 788-182

Basic relay; Nominal input voltage: 12 VDC; 1 changeover contact

www.wago.com/788-182





 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden


Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.





Data sheet | Item number: 788-182

www.wago.com/788-182



Data

Technical Data

Control circuit

Nominal input voltage U_N DC 12 V

Load circuit:

Number of changeover/switchover contacts	1
Contact material (relay)	AgCdO
Limiting continuous current	16 A
Max. switching voltage	AC 250 V
Max. switching power (resistive)	AC 4000 VA
Pull-in time (typ.)	9 ms
Drop-out time (typ.)	3 ms

Safety and protection:

Dielectric strength, control/load circuit (AC, 1 min)	5 kVrms
Dielectric strength open contact (AC, 1 min)	1 kVrms
Protection class	IP40

Geometrical Data

Width 12.7 mm / 0.5 inch

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.





Data sheet | Item number: 788-182

www.wago.com/78	8-182
-----------------	-------

Height from the surface 25.5 mm / 1.004 inch

Depth 29 mm / 1.142 inch

Mechanical data

Type of mounting Pluggable module

Material Data

Weight 18 g

Environmental Requirements

Surrounding air (operating) temperature at U _N	-40 85 °C	
Surrounding air (storage) temperature	-40 85 ℃	

Standards and specifications

Standards/specifications EN 61810-1

Commercial data

Product Group	6 (Interface Electronics)
Packaging type	BOX
Country of origin	CZ
GTIN	4050821867944
Customs Tariff No.	85364900990

Counterpart

Downloads

Documentation

Additional Information

Disposal; Electrical and electronic equipment, Packaging V 1.0.0 pdf Download 265.8 kB

CAD/CAE-Data

CAE data

WSCAD Universe 788-182

Subject to changes. Please also observe the further product documentation!

WAGO Kontakttechnik GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.



MAGO

Data sheet | Item number: 788-182

www.wago.com/788-182

URL Download

Installation Notes

 $\label{thm:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO Kontakttechnik GmbH & Co. KG Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.